



Multi-Zone Gas Detector Control Panel

Up to 128 Sensors • Fully Configurable Settings
• BACnet IP & Modbus RTU Outputs



Limitless Possibilities

- Fully Configurable Zones, Relays, Setpoints, Delays, and Outputs
- Scalable System Size via Relay Expansion Packs

Increased Control

- On-Demand Ventilation Control by Gas Concentration, Timer Schedule, or User Input
- 7" Full-Color LCD Touch Screen

Maximum Detection

- Monitors up to 128 CO and/or NO₂ Sensors

Enhanced Durability

- NEMA 4X Water and Dust Resistance

Intelligent Connectivity

- BACnet IP and Modbus RTU Communication for BMS Interfacing

Simplified Installation

- Customized Factory Programming and Configuration for Every Job

Remote Sensors

Voltage	CO	NO ₂	CO/NO ₂
24 VAC	GDCP-CM-Remote	GDCP-ND-Remote	GDCP-NCM-Remote

Accessories

Voltage	Model	Description
115 VAC	GDCP-PowerPack	115 VAC to 20 VAC Adapter for GDCP-Touch and Other Accessories
24 VAC	GDCP-ExpansionPack	Expansion Pack with 4 Additional Relays



GDCP-Touch Detailed Specifications

Input/Output	
Input Power	24 VAC, 50/60 Hz, 1.0 A Optional: 120 VAC, 50/60 Hz, 0.2 A via GDCP-PowerPack
Power Consumption	24 VA
Control Relays	4 relays, 5A @ 125 VAC / 250 VA Optional: Up to 32 relays via GDCP-ExpansionPacks
Analog Outputs	User-selectable 4-20 mA, 0.2-1 VDC, 1-5 VDC, or 2-10 VDC
Digital Outputs	BACnet IP, Modbus RTU
Environmental	
Storage Temperature	-50°C to 120°C (-58°F to 248°F)
Operating Temperature	-20°C to 70°C (-4°F to 158°F)
Humidity	10% to 90% (non-condensing)
Interface	
Display	7.0" LCD, 1024 x 600, 5-point capacitive touch
Alarm	70 dB @ 10 cm, 2.9 kHz piezoelectric element
General	
Sensor Capacity	Up to 30 remote sensors Optional: Up to 128 remote sensors via GDCP-ExpansionPacks
Dimensions	8.15" W x 9.93" H x 2.70" D (21 cm W x 25 cm H x 7 cm D)
Weight	5.0 lbs (2.27 kg)
Housing	Gray, NEMA 4X, fiberglass/polycarbonate
Compliance	
Performance	Pending
Electromagnetic Interference	Pending
Environmental	Pending

DISCLAIMER: The information in this preliminary document is subject to change without notice and should not be construed as a commitment by Brasch Environmental Technologies, LLC. Brasch assumes no responsibility for any errors that may appear in this document. In no event shall Brasch be liable for incidental or consequential damages arising from the use of this document.